# SONY

#### Catalog No. 380

## **LASERSCALE**<sub>TM</sub>

Scale Display Detector **BR10A BD11/15 BS75A/76 BD60** 



# The BS75A and BS76 Series are high-accuracy laser scales with a low expansion coefficient that provides reliable, hith-precision measuring with a resolution selectable from 0.01 $\mu$ m, 0.05 $\mu$ m and 0.1 $\mu$ m.

- Comparable to the laser interferometer in accuracy and As easy to handle as Magnescale (installation/adjustresolution.
- 0.1 + 0.4L/100 (µm p-p) or less (BS75A/76-N Series)
  - L = measuring length (mm)
- The scale glass used has an expansion coefficient of -0.7 × 10<sup>-6°</sup>C<sup>-1</sup>
- Selectable accuracy and resolution according to the application.
- Resolution: 0.01 µm (when used with BR10A/BD11)
  - 0.0086... µm (when used with BR10A/BD15) 0.1  $\mu m$  (when used with BD60)
- Measuring length: 30 mm to 410 mm /1.2" to 16.1"
  - (covered by 9 models)

- ment) and just as reliable.
- Accuracy: 0.05 + 0.2L/100 (µm p-p) or less (BS75A/76-NS Series) Little affected by disturbed air and changing atmospheric pressure.
  - Usable in vacuum of up to 10<sup>-5</sup> Pa:
  - Uses vacuum resistant material. Various interface modes.

#### Major applications

- Semiconductor manufacturing machines, inspection equipment.
- Precision machine tools.
- Precision measuring tools, testing instruments.

#### BS75A/76 scale unit

Model	BS75A		BS76	
	-30NS to -410NS	-30N to -410N	-30NS to -410NS	-30N to -410N
Measuring length (L)	30/60/110/160/210/260/310/410 (mm) 1.2/2.3/4.3/6.2/8.2/10.2/12.2/16.1 (inch)			
Overall length	L + 36 mm/1.4"			
Max. travel	L + 10 mm/0.39" (5 mm/0.20" on both ends)			
Accuracy (at 20°C/68°F) (L:mm)	0.05+0.2L/100 (μm p-p) or less	0.1+0.4L/100 (μm p-p) or less	0.05+0.2L/100 (μm p-p) or less	0.1+0.4L/100 (μm p-p) or less
Return error	0.02 μm (with 0.01 μm-resolution) 0.05 μm (with 0.05 μm-resolution)			
Repeatability	0.01 μm (2σ) (with 0.01 μm-resolution) 0.05 μm (2σ) (with 0.05 μm-resolution)			
Expansion coefficient	-0.7 × 10 <sup>-6</sup> °C <sup>-1</sup>			
Light source	Semiconductor laser			
Detection method	Diffracting grating scan			
Use in vacuum	Possible up to 10 <sup>-5</sup> Pa		p to 10⁻⁵ Pa	
Design	Exposed scale			
Operating temperature	+10°C to 30°C/+50°F to 86°F (condensation not allowed)			
Storage temperature	-10°C to 50°C/+14°F to 122°F			
Cable length	3 m (st	andard)	2 m in v 3 m in the a	acuum atmosphere
Mass	0.44/0.44/0.45/0.46/0.47/0.48/0.49/0.50/0.51 (kg) 0.97/0.97/0.99/1.01/1.04/1.06/1.08/1.10/1.12 (lbs)			

#### BR10A display unit

Model		Madel	BR10A			
		wodei	-1F11	-1F12	-1F13	-1F14
No. of display axes		of display axes	1 axis			
С	)ut	put resolution		0.008	36 µm	
Display resolution			Switch selectable 0.01/0.05 µm and double counting			
N	lax	. response speed	120 mm/s (4.7"/s)			
Display technology		blay technology	VFD vacuum fluorescent display tube (white display) Minus sign and 8 digits, mode indication			
Display range		olay range	±999.99999 mm (±9.9999995") with 0.01 μm resolution			
Scale pitch compensation		le pitch compensation	Presettable 0.1379			
Reset/Preset/Recall		et/Preset/Recall	Reset, preset, recall			
Alarm		m	<ol> <li>Power interrupt</li> <li>Max. response speed exceeded</li> <li>Data backup error</li> <li>Break in the head cable or head cable disconnected</li> <li>Compensation value not set ("0000")</li> <li>Reset by resupplying power or RESET signal.</li> </ol>			
		RS-232C (with pitch com- pensation ⇒ displayd value)		•	•	
e	م	Quadrature A/B phase (with pitch compensation)				•
terfac	andai	GP-IB (with pitch compen- sation ⇒ displayd value)	•		•	
Ē	м Г	Quadrature output (without pitch compensation)	•	•	•	
		32-bit parallel binary output (with pitch compensation)	•	•	•	•
Power supply		er supply	100/110V AC ± 10%, 220/240V AC ± 10%, 50/60 Hz			
Power consumption		er consumption	70 VA max.			
Operating temperature		rating temperature	0°C to 40°C/32°F to 104°F			
Storage temperature		age temperature	-10°C to 50°C/14°F to 122°F			
Humidity		nidity	No condensation			
Dimensions mm (inch)		ensions mm (inch)	$320 \times 100 \times 290 \ (12.6 \times 3.9 \times 11.4)$			
Mass kg (lbs)		e ka (lbe)	57(126)			

#### BD15/BD11 detector

Madal	DD45	BD11		
Model	6108	-1F14	-1F16	-2F16
No. of connectable axes		1 2		2
Resolution	0.0086µm	0.01 μm		
Output pulse width	See Note below.	Min. 200 ns		
Max. response speed	120 mm/s (4.7"/s)	30 mm/s (1.1"/s)		
Quadrature A/B output (without pitch compensation)	•			
Quadrature A/B output (with pitch compensation)		•	•	•
32-bit parallel binary (with pitch compensation)		•		
Zero point signal		•	•	•
Output circuit	Voltage-differential line d	river SN75113 (or equivalent)		
Scale pitch compensation		Real-time scale pitch compensation		
Alarm	1. Max response speed exceeded.     2. Break in the head cable or head cable disconnected.     3. Compensation value not set ("0000").     Reset by resupplying power or RESET signal.			
Reset	Via external reset connector			
Power supply	+5V DC $\pm$ 5%, $\pm$ 12V DC $\pm$ 5%	100V AC 220V AC to	to 120V A0 240V AC ± 10	C ± 10%, 0%, 50/60Hz
Power consumption	5.7 W max.	26 VA max.		
Operating/Storage temperature	0°C to 40C°/-10C° to +50°C 32°F to 104F°/14F° to 122°F	0°C to 50C*/-10C° to +60°C 32°F to 122F°/14F° to 140°F		
Dimensions mm (inch)	20 × 172.2 × 261.8 (0.79" × 10.31" × 6.78")	$\begin{array}{c} 55 \times 250 \times 320 \\ (2.2'' \times 9.8'' \times 12.6'') \end{array}$		
Mass kg (lbs)	0.3 (0.66)	3.4 (7.50)		

\*For the detailes of output pulse width of BD15, consult your nearest distributer of ours.

#### BD60 detector

Model	BD60
No. of connectable axes	1
Resolution	0.1 μm
Output pulse width	Min. 200 ns
Max. response speed	300 mm/s (11.8"/s)
Output signal	● Quadrature output (pitch-compensated) ● Zero point signal output ● Alarm signal
Output circuit	Voltage-differential line driver SN75113 (or equivalent)
Scale pitch compensation	Preset 0.1379
Alarm	<ol> <li>Scale's max. response speed exceeded.</li> <li>Break in the head cable or head cable disconnected.</li> <li>Compensetion value not set ("0000").</li> <li>Reset by resupplying power or RESET signal.</li> </ol>
Reset	Resupply power, use RESET switch or external reset input.
Power supply	+24V* DC±10%
Power consumption	10W max.
Operating temperature	0°c to 50C°/32F° to 122°F
Storage temperature	-10°c to 60C°/14F° to 140°F
Dimensions mm (inch)	$32 \times 44 \times 171 \ (1.26 \times 1.73 \times 6.7)$
Mass kg (Ibs)	0.8 (1.76)

\*For +12V/+5V operation, consult your nearest distributor of ours.



### Sony Precision Technology Inc.

Toyo Building, 9-17, Nishigotanda 3-chome, Shinagawa-ku, Tokyo, 141-0031 Japan Phone: +81-3-3490-9481 Fax: +81-3-3490-8028 http://www.sonypt.co.jp/

SONY is a registered trademark, and is used by Sony Precision Technology Inc. under license from Sony Corporation. Description of this brochure is based on the specifications as of February 2000.